

PT300E

Stationary Generator Monitoring System



The PT300E generator monitoring system is a full featured solution for any residential, commercial or industrial indoor or outdoor standby generator. This monitor includes a custom harness, has four (4) additional programmable bias inputs and one (1) ADC input. The PT300E digital inputs are used with generator controller outputs and accessory kits. When configured with the appropriate accessory kits, the PT300E can log the full sequence of operation of the emergency power system.



Standard Unit Includes

- PT300E Monitor – Fully Configured & Scripted
- External Cellular & GPS Antenna
- Custom Connection Harness
- 4 Digital Inputs
- 1 ADC Input
- 3 Relay Driver Outputs
- 7-32VDC Power
- Cellular Carrier Activation
- Over-The-Air Unit Configuration and Updates
- Generator On (Running)/Generator Off (Stopped)
- Engine Battery Voltage Monitor with Low Battery Alarm
- Generator Failed to Exercise (Missed Exercise Cycle)
- Extended Run Time Alerts - Generator Running for 4, 8, 12 & 24 Hours
- Remote Start Relay Driver Output (Customer Furnished Relay)

Input Configuration

The PT Series of monitoring systems are **UNIVERSAL** to all brands, models, ages, and sizes and provide extensive flexibility when selecting what conditions to monitor. Typically, there are relay outputs available on the generator, some may even be programmable. The PT Series of monitoring systems allow you to cost effectively utilize available output contacts on the generator to monitor critical alarms and conditions.

All PT Series monitoring systems include a “Generator On/Off” engine run signal and a battery voltage monitor with low battery alarm. The PT Series monitors also log the exercise cycle, send an alert if the generator has “Failed to Exercise,” and provide an alert if the generator has been running for an extended period of time.

The PT300E monitoring system includes **four (4)** additional digital inputs that can be used to monitor any condition that is available from the generator outputs or from any of the optional accessory kits.

User Interface: Power Link



Power Link is the most versatile and comprehensive user interface on the market. It is designed for generator service organizations to monitor and track customer equipment and service technicians all in one place. All monitoring systems include a personalized application portal and provide extensive, customizable alerts and reports.

PT300E

Stationary Generator Monitoring System



Digital Inputs (4 Available)

The monitor programming is completely configurable and based on the inputs selected. When utilizing available output contacts on the generator, the monitoring system is able to be configured for those alarms and conditions. There are also optional accessory kits available that can be used to sense the availability of **Utility Power Voltage** (Utility Power On/Off), **Generator Output Voltage** (Generator Breaker Open/Closed) and **Generator Current** (On Generator Power).

The **PT300E** digital inputs are programmable with a high or low bias and can be used with any output contact available on the generator controller.

Utility Voltage Sensing Kit

Two types of kits are offered for Utility Voltage Sensing to log and report the events of "Utility Power On/Off." The PTK-UVD kit is a voltage detection sensor suitable for any AC voltage and connects on to a conductor to determine if AC voltage is present or not. The PTK-UVR kits include an AC voltage sensing relay and connection harness and come in voltage configurations of 120V, 208V, 240V, and 277V.

Generator Voltage Sensing Kit

The PTK-GVD kit is a voltage detection sensor suitable for any AC voltage and connects on to an output conductor on the output side of the generator breaker to determine if AC voltage is present or not when the generator is running. This kit is used to log and report the event of "Generator Breaker Open." When used in conjunction with a Utility Voltage Sensing Kit, the condition of "Site Without Power" is reported when no voltage is present from either the Utility Source or Generator.

Generator Current Sensing Kit

The PTK-GCS kit includes a split core current sensing switch that clamps around one of the generator output conductors or a stator lead to determine if current is present from the generator. This kit is used to log and report the conditions of "On Generator Power" and "On Utility Power."

ADC Input (1 Available)

The **PT300E** has one (1) ADC input channel available. This input is typically used for detecting a generator fault alarm when connected to an alarm horn or fault lamp when a common fault alarm output is not available or used with an external fuel level sensor when a low fuel level output contact is not available.

PT300E Specifications

External Cellular & GPS Antenna

Custom Plug In 48" I/O Wiring Harness with Extended 96" Power Connection Leads

Temperature: -30° to 75° C (operating)

Humidity: 95%RH @ 50° C non-condensing

Shock and Vibration: U.S. Military Standards 202G and 810F, SAE J1455

EMC/EMI: SAE J1113; FCC-Part 15B; Industry Canada RoHS Compliant

Operating Voltage: 7-32 VDC

Dimensions: 2.125 x 3.5 x 0.625", (54 x 89 x 16mm)

Weight: 2.6 oz, (74 g)

Comprehensive I/O:

- Digital Inputs: 4 programmable bias
- Digital Outputs: 3 open collector (150 mA)
- Analog Inputs: 1 external ADC and 1 internal VCC monitor (battery voltage monitor)

Status LEDs: GPS and cellular

Mount: Tie-Wrap, Velcro or Adhesive